

EN

P1PY2xx P1PX2xx

Laser Distance Sensors ToF

Winner
Automations
Best
Award 2025
powered by messtec drives Automation



Interface Description

P1PY2xx / P1PX2xx

Vendor ID

| Product | hex | dec | hex (Bytes) | dec (Bytes) |
|-----------------------|--------|-----|-------------|-------------|
| wenglor sensoric GmbH | 0x0057 | 87 | 00 57 | 0 87 |

Device ID

| Product | hex | dec | hex (Bytes) | dec (Bytes) |
|---------|----------|-----|-------------|-------------|
| P1PY201 | 0x000012 | 18 | 00 00 12 | 0 0 18 |
| P1PY203 | 0x000013 | 19 | 00 00 13 | 0 0 19 |
| P1PY207 | 0x000016 | 22 | 00 00 16 | 0 0 22 |
| P1PY208 | 0x000017 | 23 | 00 00 17 | 0 0 23 |
| P1PY210 | 0x00006F | 111 | 00 00 6F | 0 0 111 |
| P1PY217 | 0x000070 | 112 | 00 00 70 | 0 0 112 |
| P1PY218 | 0x000071 | 113 | 00 00 71 | 0 0 113 |
| | | | | |
| P1PX201 | 0x000014 | 20 | 00 00 14 | 0 0 20 |
| P1PX203 | 0x000015 | 21 | 00 00 15 | 0 0 21 |
| P1PX208 | 0x00006E | 110 | 00 00 6E | 0 0 110 |

IO-Link Information

| | |
|--------------------------------------|--------|
| IO-Link Version: | V1.1 |
| Data Storage: | Yes |
| Blockparameter: | Yes |
| Min Cycle time: | 0,8 ms |
| SIO-Mode: | Yes |
| COM-Mode: | COM3 |
| ISDU: | Yes |
| Process data In (Device to Master): | 48 Bit |
| Process data Out (Master to Device): | 8 Bit |

IO-Link Profiles

Common Profile
Smart Sensor Profil - Measuring Sensor, high resolution, SSP 3.2
Smart Sensor Profil - Transducer Disable

Process Data Input (Length: 48 Bit)

Device to Master

Index 276 = 0 --> Distance in Millimeter , Index 276 = 1 --> Distance in Inch

| Subindex | Name | Bit Offset | Length | Range |
|----------|--|------------|--------|--|
| 1 | Measurement Value: Distance in mm Distance in Inch | 16 | Sint32 | P1PY2xx: 50...10.000 mm 2,0...393,7 1/10 inch P1PY21x: 50...5.000 mm 2,0...196,9 1/10 inch P1PX2xx: 200...100.000 mm 8,0...3937 1/10 inch |
| 2 | Scale | 8 | Sint8 | - 3 = mm |
| 3 | Indication Error/Warning 4 | 7 | 1 Bit | 0 = false 1 = true |
| 4 | Indication Error/Warning 3 | 6 | 1 Bit | 0 = false 1 = true |
| 5 | Indication Error/Warning 2 | 5 | 1 Bit | 0 = false 1 = true |
| 6 | Indication Error/Warning 1 | 4 | 1 Bit | 0 = false 1 = true |
| 7 | Error | 3 | 1 Bit | 0 = false 1 = true |
| 8 | Warning | 2 | 1 Bit | 0 = false 1 = true |
| 9 | SSC1 – Switching Signal 2 | 1 | 1 Bit | 0 = false 1 = true |
| 10 | SSC1 – Switching Signal 1 | 0 | 1 Bit | 0 = false 1 = true |

These values are outside the measurement range and show information about the measurement

Measured Value Distance =
 Object too far 2147483640 0x7FFFFFFF8
 Object too close -2147483640 0x80000008
 No measurement data 2147483644 0x7FFFFFFFC

| | Octet 0 (MSB) | | | | | | | | Octet 1 | | | | | | | | Octet 2 | | | | | | | | Octet 3 | | | | | | | |
|------------|--------------------------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|
| Subindex | 1 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Bit Offset | 47 | 46 | 45 | 44 | 43 | 42 | 41 | 40 | 39 | 38 | 37 | 36 | 35 | 34 | 33 | 32 | 31 | 30 | 29 | 28 | 27 | 26 | 25 | 24 | 23 | 22 | 21 | 20 | 19 | 18 | 17 | 16 |
| | Measurement value 32 bit | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |

| | Octet 4 | | | | | | | | Octet 5 (LSB) | | | | | | | |
|------------|---------|----|----|----|----|----|---|---|---------------|---|---|---|---|---|---|----|
| Subindex | 2 | | | | | | | | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 |
| Bit Offset | 15 | 14 | 13 | 12 | 11 | 10 | 9 | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |
| | Scale | | | | | | | | | | | | | | | |

Index 276 = 2 --> Distance in mm + Speed

| Subindex | Name | Bit Offset | Length | Range |
|-----------|--------------------------------------|------------|--------|--|
| 1 | Measurement Value: Distance in mm | 24 | Sint24 | P1PY2xx: 50...10.000 mm 2,0...393,7 1/10 inch P1PY21x: 50...5.000 mm 2,0...196,9 1/10 inch P1PX2xx: 200...100.000 mm 8,0...3937 1/10 inch |
| 2 | Measurement Value: Speed in mm/s | 8 | Sint16 | -30.000...30.000 mm/s |
| 3 | Indication Error/Warning 4 | 7 | 1 Bit | 0 = false 1 = true |
| 4 | Indication Error/Warning 3 | 6 | 1 Bit | 0 = false 1 = true |
| 5 | Indication Error/Warning 2 | 5 | 1 Bit | 0 = false 1 = true |
| 6 | Indication Error/Warning 1 | 4 | 1 Bit | 0 = false 1 = true |
| 7 | Error | 3 | 1 Bit | 0 = false 1 = true |
| 8 | Warning | 2 | 1 Bit | 0 = false 1 = true |
| 9 | SSC1 – Switching Signal 2 | 1 | 1 Bit | 0 = false 1 = true |
| 10 | SSC1 – Switching Signal 1 | 0 | 1 Bit | 0 = false 1 = true |

These values are outside the measurement range and show information about the measurement

Measured Value Distance =
 Object too far 8388600 0x7FFFF8
 Object too close -8388600 0x800008
 No measurement data 8388604 0xFFFFFC

Measured Value Speed =
 Object too far --- ---
 Object too close --- ---
 No measurement data 32764 0x7FFC

| | Octet 0 (MSB) | | | | | | | | Octet 1 | | | | | | | | Octet 2 | | | | | | | | Octet 3 | | | | | | | |
|-----------------|--------------------------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|-----------------------|----|----|----|----|----|----|----|
| Subindex | 1 | | | | | | | | | | | | | | | | | | | | | | | | 2 | | | | | | | |
| Bit Offset | 47 | 46 | 45 | 44 | 43 | 42 | 41 | 40 | 39 | 38 | 37 | 36 | 35 | 34 | 33 | 32 | 31 | 30 | 29 | 28 | 27 | 26 | 25 | 24 | 23 | 22 | 21 | 20 | 19 | 18 | 17 | 16 |
| | Measured Distance 24 bit | | | | | | | | | | | | | | | | | | | | | | | | Measured Speed 16 bit | | | | | | | |

| | Octet 4 | | | | | | | | Octet 5 (LSB) | | | | | | | |
|-----------------|-----------------------|----|----|----|----|----|---|---|---------------|----------|----------|----------|----------|----------|----------|-----------|
| Subindex | 2 | | | | | | | | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 |
| Bit Offset | 15 | 14 | 13 | 12 | 11 | 10 | 9 | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |
| | Measured Speed 16 bit | | | | | | | | | | | | | | | |

Index 276 = 3 --> Distance in mm + Speed + Intensity
Only available for P1PY2xx

| Subindex | Name | Bit Offset | Length | Range |
|-----------|---|------------|--------|--|
| 1 | Measurement Value: Distance in mm | 32 | Uint16 | 50...10.000 mm 2,0...393,7 1/10 inch P1PY21x: 50...5.000 mm 2,0...196,9 1/10 inch |
| 2 | Measurement Value: Speed in mm/s | 16 | Sint16 | -30.000...30.000 mm/s |
| 3 | Measurement Value: Intensity in Digits | 8 | Uint8 | 0...255 |
| 4 | Indication Error/Warning 4 | 7 | 1 Bit | 0 = false 1 = true |
| 5 | Indication Error/Warning 3 | 6 | 1 Bit | 0 = false 1 = true |
| 6 | Indication Error/Warning 2 | 5 | 1 Bit | 0 = false 1 = true |
| 7 | Indication Error/Warning 1 | 4 | 1 Bit | 0 = false 1 = true |
| 8 | Error | 3 | 1 Bit | 0 = false 1 = true |
| 9 | Warning | 2 | 1 Bit | 0 = false 1 = true |
| 10 | SSC1 - Switching Signal 2 | 1 | 1 Bit | 0 = false 1 = true |
| 11 | SSC1 - Switching Signal 1 | 0 | 1 Bit | 0 = false 1 = true |

These values are outside the measurement range and show information about the measurement

Measured Value Distance =

| | | |
|---------------------|-------|--------|
| Object too far | 65534 | 0xFFFE |
| Object too close | 0 | 0 |
| No measurement data | 65535 | 0xFFFF |

Measured Value Speed =

| | | |
|---------------------|-------|--------|
| Object too far | --- | --- |
| Object too close | --- | --- |
| No measurement data | 32764 | 0x7FFC |

Measured Value Intensity =

| | | |
|---------------------|-----|------|
| Object too far | --- | --- |
| Object too close | --- | --- |
| No measurement data | 255 | 0xFF |

| | Octet 0 (MSB) | | | | | | | | Octet 1 | | | | | | | | Octet 2 | | | | | | | | Octet 3 | | | | | | | |
|-----------------|--------------------------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|-----------------------|----|----|----|----|----|----|----|---------|----|----|----|----|----|----|----|
| Subindex | 1 | | | | | | | | | | | | | | | | 2 | | | | | | | | | | | | | | | |
| Bit Offset | 47 | 46 | 45 | 44 | 43 | 42 | 41 | 40 | 39 | 38 | 37 | 36 | 35 | 34 | 33 | 32 | 31 | 30 | 29 | 28 | 27 | 26 | 25 | 24 | 23 | 22 | 21 | 20 | 19 | 18 | 17 | 16 |
| | Measured Distance 16 bit | | | | | | | | | | | | | | | | Measured Speed 16 bit | | | | | | | | | | | | | | | |

| | Octet 4 | | | | | | | | Octet 5 (LSB) | | | | | | | |
|-----------------|--------------------------|----|----|----|----|----|---|---|---------------|----------|----------|----------|----------|----------|-----------|-----------|
| Subindex | 3 | | | | | | | | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
| Bit Offset | 15 | 14 | 13 | 12 | 11 | 10 | 9 | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |
| | Measured Intensity 8 bit | | | | | | | | | | | | | | | |

Process Data Output (Length: 8 Bit)

Master to Device

| Subindex | Name | Bit Offset | Length | Range |
|----------|---------------|------------|--------|-------------------------|
| 1 | Emitted Light | 0 | 1 Bit | 0 = On 1 = Off |
| 2 | Find Me | 1 | 1 Bit | 0 = Off 1 = Blinking |
| 3 | Teach SSC1 | 3 | 1 Bit | 0 → 1 Start Teach |
| 4 | Teach SSC2 | 4 | 1 Bit | 0 → 1 Start Teach |

| Octet 0 (MSB) | | | | | | | | |
|---------------|---|---|---|---|---|---|---|---|
| Subindex | | | | 4 | 3 | 2 | 1 | |
| Bit Offset | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |

Parameter

Identification

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|----------------------------|-------------|-------------|-----------|-----|-------------------|--------------|---------|---------------|---------------------------|-------------------------|
| Information | | | | | | | | | | |
| Vendor Name | 10 | 16 | 0 | R | String | | | | wenglor sensoric GmbH | |
| Vendor Text | 11 | 17 | 0 | R | String | | | | the innovative family | |
| Product Name | 12 | 18 | 0 | R | String | | | | P1PY2xx P1PX2xx | |
| Product ID | 13 | 19 | 0 | R | String | | | | P1PY2xx P1PX2xx | |
| Product Text | 14 | 20 | 0 | R | String | | | | Laser Distance Sensor ToF | |
| Serial Number | 15 | 21 | 0 | R | String | | | | - | |
| Hardware Version | 16 | 22 | 0 | R | String | | | | - | |
| Firmware Version | 17 | 23 | 0 | R | String | | | | - | |
| Tags | | | | | | | | | | |
| Application Specific Tag | 18 | 24 | 0 | R/W | String 32 Byte | X | | | *** | |
| Function Tag | 19 | 25 | 0 | R/W | String 32 Byte | X | | | *** | |
| Location Tag | 1A | 26 | 0 | R/W | String 32 Byte | X | | | *** | |
| Sensor Localisation | | | | | | | | | | |
| Find Me | 1200 | 4608 | 0 | R/W | UInt8 | | X | | 0 = Off 1 = Blinking | 0 = Off 1 = Blinking |

Parameter

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|--|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|--|--|
| Device Settings | | | | | | | | | | |
| System Command | 02 | 2 | 0 | W | Uint8 | | | X | - | Device Reset = 0x80 (128) Application Reset = 0x81 (129) Restore Factory Settings = 0x82 (130) Back-to-Box = 0x83 (131) |
| Device Access Locks | 0C | 12 | 0 | R/W | Uint16 | X | | | 0 = unlocked | 0 = unlocked Bit 3 = 1: Local Parameterization locked Bit 4 = 1: User Interface Operation locked |
| Language | F0 | 240 | 0 | R/W | Uint8 | | | | 1 = English | 0 = German 1 = English 5 = Chinese |
| Display rotate | A0 | 160 | 0 | R/W | Uint8 | | | | 0 | 0 = Off 1 = On |
| Measurement Value Settings | | | | | | | | | | |
| Object Detection | 111 | 273 | 0 | R/W | Uint8 | X | | | 0 = First Object | 0 = First Object 1 = Last Object 2 = Most Intense Object |
| Measurement Mode | 110 | 272 | 0 | R/W | Uint8 | X | | | 1 = Precision | 0 = Speed 1 = Precision 2 = Precision Plus |
| Sensitivity (only P1PY2xx) | 115 | 277 | 0 | R/W | Uint8 | X | | | 0 = Maximum | 0 = Maximum 1 = Medium 2 = Low 3 = Minimum 4 = Ultra Low (Y1TA) |
| Noise Filter | D0 | 208 | 0 | R/W | Uint8 | X | | | 0 = Off | 0 = Off 1...9 |
| Emitted Light | E0 | 224 | 0 | R/W | Uint8 | X | | | 0 = On | 0 = On 1 = Off |
| Process Data Type | 114 | 276 | 0 | R/W | Uint8 | X | | X | 0 = Millimeter | P1PY2xx: 0 = Millimeter 1 = Inch 2 = Millimeter and Speed 3 = Millimeter and Speed and Intensity P1PX2xx: 0 = Millimeter 1 = Inch 2 = Millimeter and Speed |
| Detection Range Near | 112 | 274 | 0 | R/W | Int32 | X | | | 0 mm | P1PY2xx: 0...10.000 mm P1PX2xx 0... 100.000 mm |
| Detection Range Far | 113 | 275 | 0 | R/W | Int32 | X | | | P1PY2xx: 30.000 mm P1PX2xx: 130.000mm | P1PY2xx: 0...10.000 mm P1PX2xx: 0...100.000 mm P1PY21x: 0...5.000 mm |
| Switching Signal Channel 1 - SSC1 | | | | | | | | | | |
| SSC1 Teach-Mode | 290 | 656 | 0 | R/W | Uint8 | X | | X | 0 = Foreground | P1PY2xx 0 = Foreground 1 = Background 2 = Window 4 = Intensity 5 = Jump P1PX2xx 0 = Foreground 1 = Background 2 = Window 5 = Jump |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|--|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|--|---|
| SSC1 Switch Point | 270 | 624 | 0 | R/W | Int32 | X | | | P1PY2xx: 5.000 mm P1PX2xx: 10.000 | P1PY2xx: 50...10.000 mm P1PY21x: 50...5.000 mm P1PX2xx: 200...100.000 mm |
| SSC1 Hysteresis | 300 | 768 | 0 | R/W | Uint16 | X | | | 15 mm | 5...1000 mm |
| SSC1 Window (SSC1 Mode = Window) | | | | | | | | | | |
| SSC1 Window Near | 271 | 625 | 0 | R/W | Int32 | X | | | 30 mm | P1PY2xx: 1...10.000 mm P1PY21x: 50...5.000 mm P1PX2xx: 1... 100.000 mm |
| SSC1 Window Far | 272 | 626 | 0 | R/W | Int32 | X | | | 30 mm | P1PY2xx: 1...10.000 mm P1PY21x: 50...5.000 mm P1PX2xx: 1...100.000 mm |
| SSC1 Jump (SSC1 Mode = Jump Detection) | | | | | | | | | | |
| SSC1 Jump Height min | 224 | 548 | 0 | R/W | Uint32 | | | | 50 | 10...1.000 |
| SSC1 Jump Height max. | 223 | 547 | 0 | R/W | Uint32 | | | | 1000 | 0...100.000 |
| SSC1 Jump Direction | 226 | 550 | 0 | R/W | Uint8 | | | | 1 | 1 = Positive 2 = Negative 3 = Both |
| SSC1 Jump Time Delta | 225 | 549 | 0 | R/W | Uint8 | | | | 10 | 1...64 |
| SSC1 Jump Impulse | 228 | 552 | 0 | R/W | Uint16 | | | | 100 | 0 = Hold 1...1000 |
| SSC1 Intensity (SSC1 Mode = Distance+Intensity) | | | | | | | | | | |
| SSC1 Distance Window | 292 | 658 | 0 | R/W | Uin16 | | | | 50 | 0...300 |
| SSC1 Intensity Hysteresis | 294 | 660 | 0 | R/W | Uint8 | | | | 5 | 0...255 |
| SSC1 Intensity Window | 295 | 661 | 0 | R/W | Uint8 | | | | 5 | 0...255 |
| SSC1 Intensity Switch Point | 296 | 662 | 0 | R/W | Uint8 | | | | 200 | 0...255 |
| Switching Signal Channel 2 – SSC2 | | | | | | | | | | |
| SSC2 Teach Mode | 291 | 657 | 0 | R/W | Uint8 | X | | X | 0 = Foreground | P1PY2xx 0 = Foreground 1 = Background 2 = Window 4 = Intensity 5 = Jump P1PX2xx 0 = Foreground 1 = Background 2 = Window 5 = Jump |
| SSC2 Switch Point | 280 | 640 | 0 | R/W | Int32 | X | | | P1PY2xx: 5.000 mm P1PX2xx: 10.000 | P1PY2xx: 50...10.000 mm P1PY21x: 50...5.000 mm P1PX2xx: 200...100.000 mm |
| SSC2 Hysteresis | 301 | 769 | 0 | R/W | Uint16 | X | | | 15 mm | 5...1000 mm |
| SSC2 Window (SSC2 Mode = Window) | | | | | | | | | | |
| SSC2 Window Near | 281 | 641 | 0 | R/W | Int32 | X | | | 30 mm | P1PY2xx: 1...10.000 mm P1PY21x: 1...5.000 mm P1PX2xx: 1... 100.000 mm |
| SSC2 Window Far | 282 | 642 | 0 | R/W | Int32 | X | | | 30 mm | P1PY2xx: 1...10.000 mm P1PY21x: 1...5.000 mm P1PX2xx: 1...100.000 mm |
| SSC2 Jump (SSC2 Mode = Jump Detection) | | | | | | | | | | |
| SSC2 Jump Height min | 22B | 555 | 0 | R/W | Uint32 | | | | 50 | 10...1.000 |
| SSC2 Jump Height max. | 22A | 554 | 0 | R/W | Uint32 | | | | 1000 | 0...100.000 |
| SSC2 Jump Direction | 22D | 557 | 0 | R/W | Uint8 | | | | 1 | 1 = Positive 2 = Negative 3 = Both |
| SSC2 Jump Time Delta | 22C | 556 | 0 | R/W | Uint8 | | | | 10 | 1...64 |
| SSC2 Jump Impulse | 22F | 559 | 0 | R/W | Uint16 | | | | 100 | 0 = Hold 1...1000 |
| SSC2 Intensity (SSC2 Mode = Distance+Intensity) | | | | | | | | | | |
| SSC2 Distance Window | 293 | 659 | 0 | R/W | Uint16 | | | | 50 | 0...300 |
| SSC2 Intensity Hysteresis | 297 | 663 | 0 | R/W | Uint8 | | | | 5 | 0...255 |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|--|-------------|-------------|-------------|-----|----------|--------------|---------|---------------|--|---|
| SSC2 Intensity Window | 298 | 664 | 0 | R/W | Uint8 | | | | 5 | 0...255 |
| SSC2 Intensity Switch Point | 299 | 665 | 0 | R/W | Uint8 | | | | 200 | 0.. 255 |
| Teach-In | | | | | | | | | | |
| SSC1 Teach-In | 200 | 512 | 0 | W | Uint8 | | | X | 0 | 0 = No Teach-In 1 = Do Teach-In |
| SSC2 Teach-In | 201 | 513 | 0 | W | Uint8 | | | X | 0 | 0 = No Teach-In 1 = Do Teach-In |
| Teach-In Status | 20F | 527 | 1 2 4 | R | Uint8 | | | | 0 false false | 0 = Idle 1 = Success 5 = Busy 7 = Error |
| Pin Function | | | | | | | | | | |
| E/A1 Pin Function | 40 | 64 | 0 | R/W | Uint8 | X | | X | 0 = Switching Output | 0 = Switching Output SSC1 1 = Error Output 2 = Warning Output 3 = Emitted Light Disengageable 4 = Extern Teach 5 = Disabled |
| E/A2 Pin Function | 41 | 65 | 0 | R/W | Uint8 | X | | X | P1PY201 / P1PX201 P1PY203 / P1PX203: 0 = Switching Output | 0 = Switching Output SSC2 1 = Error Output 2 = Warning Output 3 = Emitted Light Disengageable 4 = Extern Teach 5 = Disabled 6 = Antivalent Switching Output |
| E3 Pin Function | 42 | 66 | 0 | R/W | Uint8 | X | | X | 3 = Emitted Light Disengageable | 3 = Emitted Light Disengageable 4 = Extern Teach 5 = Disabled |
| Digital Outputs | | | | | | | | | | |
| A1 (SSC, Error or Warning Output) | | | | | | | | | | |
| A1 On Delay | 50 | 80 | 0 | R/W | Uint16 | X | | | 0 ms | 0...10.000 ms |
| A1 Off Delay | 60 | 96 | 0 | R/W | Uint16 | X | | | 0 ms | 0...10.000 ms |
| A1 NO/NC | 210 | 528 | 0 | R/W | Uint8 | X | | | 0 = NO | 0 = NO 1 = NC |
| A1 NPN/PNP/P-P | 220 | 544 | 0 | R/W | Uint8 | X | | | P1PY201 / P1PX201 / P1PY207 / P1PY208 / P1PY210 / P1PY217 / P1PY218 / P1PX208: 0 = PNP | 0 = PNP 1 = NPN 2 = Push-Pull |
| | | | | | | | | | P1PY203 / P1PX203 1 = NPN | |
| A2 (SSC, Error or Warning Output) | | | | | | | | | | |
| A2 On Delay | 51 | 81 | 0 | R/W | Uint16 | X | | | 0 ms | 0...10.000 ms |
| A2 Off Delay | 61 | 97 | 0 | R/W | Uint16 | X | | | 0 ms | 0...10.000 ms |
| A2 Config.Logic | 211 | 529 | 0 | R/W | Uint8 | X | | | 0 = NO | 0 = NO 1 = NC |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|--|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|---|--|
| A2 NPN/PNP/P-P | 221 | 545 | 0 | R/W | UInt8 | X | | | P1PY201 / P1PX201 0 = PNP P1PY203 / P1PX203 1 = NPN | 0 = PNP 1 = NPN 2 = Push-Pull |
| Digital Inputs | | | | | | | | | | |
| E1 (Teach Input or Emitted Light) | | | | | | | | | | |
| E1 Input Ub Active/Inactive | 0260 | 608 | 0 | R/W | UInt8 | X | | | 0 = Ub active | 0 = Ub Active 1 = Ub Inactive |
| E2 (Teach Input or Emitted Light) | | | | | | | | | | |
| E2 Input Ub Active/Inactive | 261 | 609 | 0 | R/W | UInt8 | X | | | 0 = Ub active | 0 = Ub Active 1 = Ub Inactive |
| E3 (Teach Input or Emitted Light) | | | | | | | | | | |
| E3 Input Ub Active/Inactive | 262 | 610 | 0 | R/W | UInt8 | X | | | 0 = Ub active | 0 = Ub Active 1 = Ub Inactive |
| Analog Outputs | | | | | | | | | | |
| Analog Outputs (P1Px2x7, P1Px2x8) | | | | | | | | | | |
| O Analog Teach-In Analog | 80 | 128 | 0 | W | UInt8 | | | X | 0 | 0 = No Teach-In 1 = Do Teach 0 V / 4 mA 2 = Do Teach 10 V / 20 mA |
| O Analog 0 V / 4 mA | 81 | 129 | 0 | R/W | UInt32 | X | | | P1PY2xx: 50 mm P1PX2xx: 200 mm | P1PY2xx: 50...10.000 mm P1PY21x: 50...5.000 mm P1PX2xx: 200...100.000 mm |
| O Analog 10 V / 20 mA | 82 | 130 | 0 | R/W | UInt32 | X | | | P1PY2xx: 10.000 mm P1PY21x: 5.000 mm P1PX2xx: 100.000 mm | P1PY2xx: 50...10.000 mm P1PY21x: 50...5.000 mm P1PX2xx: 200...100.000 mm |
| O Analog Substitute Values | 84 | 132 | 0 | R/W | UInt8 | X | | | P1Px2x8 / P1PY210: 1 = Enabled P1Px2x7: not available | 0 = Disabled 1 = Enabled |
| Bluetooth | | | | | | | | | | |
| Bluetooth | 306 | 774 | 0 | R/W | UInt8 | | | | 0 | 0 = On 1 = Off |
| Password Protection | 100 | 256 | 0 | R/W | UInt8 | | | | 0 | 0 = Disabled 1 = Enabled |
| Password change | 101 | 257 | 0 | R/W | String32 | | | | *** | |
| Bluetooth Firmware | 1401 | 5121 | 0 | R | String32 | | | | *** | |
| Bluetooth Address | 1403 | 5123 | 0 | R | String32 | | | | *** | |
| Bluetooth GUI Version | 140A | 5130 | 0 | R | UInt32 | | | | 0 | |
| Bluetooth Description Version | 140B | 5131 | 0 | R | UInt32 | | | | 0 | |
| Speed Measurement | | | | | | | | | | |
| Speed Threshold | 230 | 560 | 0 | R/W | UInt16 | | | | | 0...30.000 |
| Speed Direction | 231 | 561 | 0 | R/W | UInt8 | | | | 0 | 0 = Both 1 = Direction closer 2 = Direction farther |
| Speed Hysteresis | 232 | 562 | 0 | R/W | UInt16 | | | | 10 | 1...60.000 |
| Speed Filter | 233 | 563 | 0 | R/W | UInt16 | | | | 1 | 0 = Off 1 = Automatic 2...16 |

Observation

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|---|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|---------------|--|
| Object Information Access | 1210 | 4624 | 0 | R/W | UInt8 | X | | | 0 | 0 = Disabled 1 = Enabled |
| Object Information (only if enabled) | | | | | | | | | | |
| Object Detection Status | 1211 | 4625 | 1 | R | UInt8 | | X | | 0 | 0 = Object 1 ... 3 = Object 4 255 = No Object |
| Distance Object 1 | | | 2 | R | Sint32 | | X | | 0 | P1PY2xx: 50...10.000 mm |
| Distance Object 2 | | | 3 | R | Sint32 | | X | | 0 | |
| Distance Object 3 | | | 4 | R | Sint32 | | X | | 0 | |
| Distance Object 4 | | | 5 | R | Sint32 | | X | | 0 | |
| Signal Object 1 | | | 6 | R | UInt8 | | X | | 0 | P1PY21x: 50...5.000 mm P1PX2xx: 50...100.000 mm 2147483644 = No object detected -2147483640 = Too close 2147483640 = Too far |
| Signal Object 2 | | | 7 | R | UInt8 | | X | | 0 | |
| Signal Object 3 | | | 8 | R | UInt8 | | X | | 0 | |
| Signal Object 4 | | | 9 | R | UInt8 | | X | | 0 | |

Diagnosis

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|-------------------------------|-------------|-------------|-----------|-----|-------------------------|--------------|---------|---------------|---------------|---|
| Status | | | | | | | | | | |
| Device Status | 0x0024 | 36 | 0 | R | UInt8 | | X | | 0 | 0 = Device is OK 1 = Maintenance required 2 = Out of specification 3 = Functional check 4 = Failure |
| Detailed Device Status | 0x0025 | 37 | 0 | R | Array of OctectStringT3 | | X | | 0 | Shows the pending Events (maximum 4) |
| Additional Status Information | 1300 | 4864 | 0 | R | UInt32 | | X | | 0 | Value 0 = No Warning / Errors Measurement: Bit 0 = Signal Warning Bit 1 = Contamination optics Bit 2 = Contamination in range Bit 3 = Ambient light to high Bit 4 = Object to Close Bit 5 = Object to Far Bit 6 = No Measurement data Bit 8 = Emitted Light off Other: Bit 17 = Fatal Device Error Bit 18 = Temperature Error Bit 19 = Temperature Warning High Bit 20 = Temperature Warning Low Bit 21 = Analog Output Error (if implemented) Bit 22 = Velocity Sensor (if implemented) Bit 28 = Undervoltage detection Bit 29 = Short Circuit Bit 30 = Speed |
| Self Check | 2518 | 9496 | 0 | R | UInt32 | | X | | - | - |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|---|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|---------------|--|
| Condition Monitoring Configuration | | | | | | | | | | |
| Process Data Indication | | | | | | | | | | |
| Indication Error/Warning 1 | 1310 | 4880 | 0 | R/W | Uint8 | X | | | 0 | 31 = No Warning / Error Mapped Measurement: 0 = Signal Warning 1 = Contamination Optic 2 = Contamination Range 3 = Ambient Light 4 = Object Too Close 5 = Object Too Far 6 = No Measurement Data 8 = Emitted Light Off Other: 17 = Fatal Error 18 = Temperature Error 19 = Temperature Warning High 20 = Temperature Warning Low 21 = Analog Output Error (if implemented) 22 = Velocity Sensor (if implemented) 28 = Undervoltage 29 = Short Circuit 30 =Speed |
| Indication Error/Warning 2 | 1311 | 4881 | 0 | R/W | Uint8 | X | | | 1 | |
| Indication Error/Warning 3 | 1312 | 4882 | 0 | R/W | Uint8 | X | | | 3 | |
| Indication Error/Warning 4 | 1313 | 4883 | 0 | R/W | Uint8 | X | | | 19 | |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|------------------------------|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|--|---|
| Warning Output Configuration | 1314 | 4884 | 0 | R/W | Uint32 | X | | | P1PY201 P1PY203 P1PX201 P1PX203 1 2 3 4 5 6 7 9 18 19 20 21 10 29 30 P2PY207, P1PY208: additional 22 23 | 0 = Not use as Warning / Error 1 = Used as Warning / Error Measurement: Bit 0 = Signal Warning Bit 1 = Contamination Optic Bit 2 = Contamination Range Bit 3 = Ambient Light Bit 4 = Object Too Close Bit 5 = Object Too Far Bit 6 = No Measurement Data Bit 8 = Emitted Light Off Other: Bit 17 = Fatal Error Bit 18 = Temperature Error Bit 19 = Temperature Warning High Bit 20 = Temperature Warning Low Bit 21 = Analog Output Error (if implemented) Bit 22 = Velocity Sensor (if implemented) (if implemented) Bit 28 = Undervoltage Bit 29 = Short Circuit Bit 30 = Acceleration Sensor (if implemented) |
| Error Output Configuration | 1315 | 4885 | 0 | R/W | Uint32 | X | | | P1PY201 P1PY203 P1PX201 P1PX203 1 2 3 4 5 6 7 9 18 19 20 21 10 29 30 P2PY207, P1PY208: additional 22 23 | |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|---|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|-----------------------------|---|
| Measuring Data Channel | | | | | | | | | | |
| MDC Descr.Lower Limit | 4080 | 16512 | 1 | R | Int32 | | | | 50 | 50 mm / 19 1/10 inch |
| MDC Descr.Upper Limit | | | 2 | R | Int32 | | | | 10.000 | 10.000 mm / 3938 1/10 inch |
| MDC Descr.Unit Code | | | 3 | R | UInt16 | | | | 1010 = Meter 1019 = inch | 1010 = Meter 1019 = inch |
| MDC Descr.Scale | | | 4 | R | Int8 | | | | -3 | 10 ⁻³ Meter = mm / 10 ⁻¹ = 1/10 inch |
| Device Simulation | | | | | | | | | | |
| Simulation Mode | 310 | 784 | 0 | R/W | UInt8 | | X | | 0 | 0 = Off 1 = On |
| Device Simulation Enabled (Simulation Mode= 1) | | | | | | | | | | |
| Simulation Measurement Value | 315 | 789 | 0 | R/W | UInt32 | | X | | 2147483645 | P1PY2xx: 50... 10.000 12345 = Too Far 30001 = No MeasurementData P1PX2xx: 50..100.000 123456 = Too Far 130001 = No MeasurementData 0 = TooClose 2147483645 = Use Process Value |

| Name | Index (hex) | Index (dec) | Sub-index | R/W | Datatype | Data Storage | Dynamic | Modify others | Default value | Range |
|--|-------------|-------------|-----------|-----|----------|--------------|---------|---------------|-------------------|---|
| Status | | | | | | | | | | |
| Simulation SSC1 | 331 | 817 | 0 | R/W | Uint8 | | X | | 2 | 0 = Off 1 = Active 2 = Use Process Value |
| Simulation SSC2 | 332 | 818 | 0 | R/W | Uint8 | | X | | 2 | 0 = Off 1 = Active 2 = Use Process Value |
| Simulation Analog Output Voltage (P1PY2x7, P1PY2x8, P1PX208) | 316 | 790 | 0 | R/W | Uint8 | | X | | Use Process Value | P1PY2x7: 10,1 V = Use Process Value 0...10 V (values transferred in 1/10 V) P1PX2x8: 21,1 mA = Use Process Value 3,5...21,0 mA (values transferred in 1/10 mA) |
| Simulation Signal Warning | 31B | 795 | 0 | R/W | Uint8 | | X | | 2 | 0 = Off 1 = Active 2 = Use Process Value |
| Simulation Contamination Optic | 31C | 796 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Contamination Range | 31D | 797 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Ambient Light | 31E | 798 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Fatal Error | 323 | 803 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Temperature Error | 324 | 804 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Temperature Warning High | 325 | 805 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Temperature Warning Low | 32C | 812 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Analog Output Error (only P1Px2x7, P1Px2x7) | 326 | 806 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Undervoltage | 327 | 807 | 0 | R/W | Uint8 | | X | | 2 | |
| Simulation Short Circuit | 328 | 808 | 0 | R/W | Uint8 | | X | | 2 | |

Events

| Name | Event Code | Type | Specification |
|--|------------|--------------|---------------|
| Maintenance required – Cleaning | 0x8C40 | Notification | IO-Link |
| General malfunction – unknown error | 0x1000 | Error | IO-Link |
| Short circuit – Check installation | 0x7710 | Error | IO-Link |
| Device temperature over-run – Clear source of heat | 0x4210 | Warning | IO-Link |
| Device temperature under-run – Insulate device | 0x4220 | Warning | IO-Link |
| Temperature fault – Overload | 0x4000 | Error | IO-Link |
| Primary supply voltage under-run – Check tolerance | 0x5111 | Warning | IO-Link |