

Notice of Discontinuation

CP08MHT80

Laser Distance Sensor Triangulation



EN

End-of-Life Notices

Discontinued product: CP08MHT80

Recommended Replacement Product: P1PC011
P1PC012

Discontinuation effective: 30.04.2027

Key Differences

In the successor model, the optical axis has been shifted.

On the successor product, the analog output cannot be switched between 4...20 mA and 0...10 V.

On the successor product, the switching point can be readjusted via the control panel, all other functions can be set via NCF or IO-Link.

The successor product has a 5-pin M12 plug. The existing connection equipment can continue to be used with the ZC4P003 adapter.

The successor product has a configurable error output via IO-Link.

In the successor product, mounting is no longer done using slotted holes.

The successor product has an IO-Link interface instead of RS-232.

Below is a detailed product comparison:

	Discontinued Product CP08MHT80	Successor Product P1PC012	Successor product P1PC011
Optical Data			
Working Range	30...80 mm	30...80 mm	30...80 mm
Measuring Range	50 mm	30...80 mm	30...80 mm
Reproducibility maximum	60 µm	30 µm	30 µm
Reproducibility: 1 Sigma	20 µm	3 µm	3 µm
Linearity Deviation	80 µm	80 µm	80 µm
Light Source	Laser (red)	Laser (red)	Laser (red)
Wavelength	660 nm	655 nm	655 nm
Service Life (T = +25 °C)	100000 h	100000 h	100000 h
Laser Class (EN 60825-1)	2	1	1
Max. Ambient Light	10000 Lux	10000 Lux	10000 Lux
Technical Specifications			
Supply Voltage	18...30 V DC	18...30 V DC	18...30 V DC
Current Consumption (U _b = 24 V)	< 80 mA	< 35 mA	< 35 mA
Switching Frequency		650 Hz	650 Hz
Measuring Rate	1500 /s	2500 /s	2500 /s
Measuring Rate (Resolution-Mode)	600 /s		
Response Time	< 660 µs	< 0.77 ms	< 0.77 ms
Response Time (Resolution Mode)	< 1660 µs		
Temperature Drift	< 15 µm/K	< 7.5 µm/K	< 7.5 µm/K
Temperature Range	-25...50 °C	-25...50 °C	-25...50 °C

	Discontinued Product CP08MHT80	Successor Product P1PC012	Successor product P1PC011
Analog Output	0...10 V	0...10 V	4...20 mA
Load Current Voltage Output	< 1 mA		
Current Output Load Resistance	< 500 Ohm		
Switching Output Voltage Drop		< 1.5 V	< 1.5 V
Switching Output/Switching Current		100 mA	100 mA
Short Circuit Protection		yes	yes
Reverse Polarity Protection		yes	yes
Overload Protection		yes	yes
Interface	RS-232	IO-Link NFC	IO-Link NFC
Transmission rate	38400 Bd		
Protection Class	III	III	III
FDA Accession Number	0820588-000	2512215-000	2512215-000
Mechanical Data			
Setting Method	Teach-In	Teach-In NFC	Teach-In NFC
Housing Material	Plastic, ABS Plastic, PC	Plastic, ABS	Plastic, ABS
Optic Cover	Plastic, PMMA	Plastic, PMMA	Plastic, PMMA
Degree of Protection	IP67	IP67 IP68	IP67 IP68
Connection	M12 × 1; 8-pin	M12 × 1; 5-pin	M12 × 1; 5-pin
General Specifications			
Scope of delivery	1 × initial start-up instructions 1 × laser warning sign 1 × sensor	1 × Z1PE002 mounting set 1 × initial start-up instructions 1 × sensor	1 × Z1PE002 mounting set 1 × initial start-up instructions 1 × sensor
Output Functions			
Output	Analog Output Error Output	Analog Output PNP	Analog Output PNP
Circuit		NO	NO
Adjustable Parameters			
Output		Error Output Push-pull NPN PNP	Error Output Push-pull NPN PNP
Circuit		NC NC/NO NO	NC NC/NO NO
Other parameters	Scale analog output Exposure time Filter Laser light Resolution mode Speed mode	Exposure time Laser light Switching hysteresis Teach-in mode Off-delay On-delay	Exposure time Laser light Switching hysteresis Teach-in mode Off-delay On-delay

light spot diameter

CP08MHT80

Working Distance	30 mm	-	80 mm
Spot Size	0,5 × 1 mm	-	1 × 2 mm

P1PC012




Working Distance	30 mm	50 mm	80 mm
Spot Size	0,8 × 2,1 mm	0,5 × 1,7 mm	1,0 × 2,0 mm

P1PC011

Working Distance	30 mm	50 mm	80 mm
Spot Size	0,8 × 2,1 mm	0,5 × 1,7 mm	1,0 × 2,0 mm

Product Images/Technical Drawings/Connection Diagrams/Certifications

	Discontinued Product CP08MHT80	Successor Product P1PC012 P1PC011
Product Image		
Dimensioned image	<p>① Transmitter Diode ② Receiver Diode Screw M4 = 0.5 Nm</p>	<p>① Transmitter Diode ② Receiver Diode Screw M4 = 0.5 Nm</p>
control panel	<p>P7</p> <p>03 = Error Indicator 07 = Selector Switch 12 = Analog Output Indicator 24 = Plus Button 25 = Minus Button 63 = Analog Output Current Indicator</p>	<p>X12</p> <p>5a = Switching Status Indicator, O1 68 = Power LED 7c = Analog Output Indicator, AO 60 = display 06 = Teach Button</p>

	Discontinued Product CP08MHT80	Successor Product P1PC012 P1PC011
connection diagram	<p data-bbox="614 302 654 324">529</p> 	<p data-bbox="1045 302 1157 324">P1PC012</p>  <p data-bbox="1045 672 1476 862"> 1 = Supply voltage + 2 = Analog output, 0...10 V 3 = Supply voltage 0 V 4 = Switching output, IO-Link, PNP, NO 5 = Input, active-high </p> <p data-bbox="1045 907 1157 929">P1PC011</p>  <p data-bbox="1045 1243 1476 1433"> 1 = Supply voltage + 2 = Analog output, 4...20 mA 3 = Supply voltage 0 V 4 = Switching output, IO-Link, PNP, NO 5 = Input, active-high </p>

	Discontinued Product CP08MHT80		Successor Product P1PC012 P1PC011	
Approvals	