Emergency Stop SwitchContact Block

SC20J01S

Part Number



- Including illumination module
- Integrated defect protection
- Narrow installation width

Technical Data

Electrical Data							
Temperature Range	-3070 °C						
Storage temperature	-5085 °C						
Service Life (nominal load)	20000 Switching Cycles						
Protective Insulation, Rated Voltage	250 V						
Mechanical Data							
Contact material	AgNi						
Service Life	20000 Switching Cycles						
Bounce time	< 10 ms						
Connection	Screw-type connection						
Clampable Wire Cross-Section	2,5 mm ²						
Safety-relevant Data							
B10d Switching Cycles	104 000						
Number of positively driven contacts	2						
Function							
Fault Protection	yes						
Lighting module	yes						
Applicable actuator	SEAL01						
Connection Diagram No.	P08						

Actuator must be ordered separately (not included in delivery)


Contact blocks are suitable for applications up to PL e per EN ISO 13849-1 and up to SIL CL 3 per EN 62061.


Complementary Products

Safety Relay SR4B3B01S, SR4D3B01S

Software







Legen	d		PT	Platinum measuring resistor	ENARS622	Encoder A/Ā (TTL)	
+	Supply Voltage +		nc	not connected	ENBR5422	_ ' '	
-	Supply Voltage 0 V		U	Test Input	ENA	Encoder A	
~	Supply Voltage (AC Voltage)		Ū	Test Input inverted	ENB	Encoder B	
Α	Switching Output (NO)		W	Trigger Input	Amin	Digital output MIN	
Ā	Switching Output (NC)		W-	Ground for the Trigger Input	Амах	Digital output MAX	
V	Contamination/Error Output (NO)		0	Analog Output	Аок	Digital output OK	
V	Contamination/Error Output (NC)		0-	Ground for the Analog Output	SY In	Synchronization In	
Е	Input (analog or digital)		BZ	Block Discharge	SY OUT	Synchronization OUT	
Т	Teach Input		Awv	Valve Output	OLT	Brightness output	
Z	Time Delay (activation)		а	Valve Control Output +	М	Maintenance	
S	Shielding		b	Valve Control Output 0 V	rsv	reserved	
RxD	Interface Receive Path		SY	Synchronization	Wire Co	e Colors according to DIN IEC 757	
TxD	Interface Send Path		SY-	Ground for the Synchronization	BK	Black	
RDY	Ready		E+	Receiver-Line	BN	Brown	
GND	Ground		S+	Emitter-Line	RD	Red	
CL	Clock		÷	Grounding	OG	Orange	
E/A	Output/Input programmable		SnR	Switching Distance Reduction	YE	Yellow	
0	IO-Link		Rx+/-	Ethernet Receive Path	GN	Green	
PoE	Power over Ethernet		Tx+/-	Ethernet Send Path	BU	Blue	
IN	Safety Input		Bus	Interfaces-Bus A(+)/B(-)	VT	Violet	
OSSD	Safety Output		La	Emitted Light disengageable	GY	Grey	
Signal	Signal Output		Mag	Magnet activation	WH	White	
BI_D+/-	Ethernet Gigabit bidirect, data line (A-D)	RES	Input confirmation	PK	Pink	
ENors422	Encoder 0-pulse 0-0 (TTL)		ED M	Contactor Monitoring	GNYE	Green/Yellow	







